


WR138G


2600M Gigabit WIFI Router



WR138G is a 2600M 11ac dual-band wireless router specially designed for villas and large apartments with over 100Mbps FTTH network. The router has built-in dual-core CPU and is equipped with DDR3 memory, which enable the system to run fast and stably. With 128MB large memory, it has a larger data cache space to guarantee game acceleration and more functions. The built-in independent PA / LNA signal enhancement module and external 8 high-gain omnidirectional antennas produce strong signal penetration performance, which truly help to achieve the full coverage of dual-band Wi-Fi in villas and large apartments. WR138G is widely used in various applications such as wireless relay, LED light / WiFi timer switch, USB sharing etc. It is an ideal router for requirement of large coverage, signal penetration and smooth surfing.



Dual-band



Dual-core CPU




Full Gigabit Ports



Extended 8x antennas



MU-MIMO



Dual wireless CPU



IPv6



Specification

Chipset	MT7621A+MT7615N+MT7615N
Memory/Storage	128MB/16MB
Interface LAN Ports	4×10/100/1000Mbps
Interface WAN Port	1×10/100/1000Mbps
External Power Supply	12VDC/1.5A
W x D x H	234×148×31mm
Certification	CE, RoHS
Button	WPS/Reset

Wireless Standards	IEEE 802.11ac/n/a 5GHz IEEE 802.11b/g/n 2.4GHz
Wireless Speeds	800Mbps(2.4GHz) 1733Mbps(5GHz)
Frequency	2.4-2.5GHz;5.15-5.25GHz
Wireless Modes	Wireless Router; WISP; AP
Antenna	4×2.4GHz 4×5GHz

Product Interface

